

# EASO STEREO CO., LTD.

E-mail: audiopro@ms10.hinet.net  
easoco@ms17.hinet.net

4F, No.951, Chung-Cheng Rd., Chung-Ho City.

Taipei. 235 Taiwan. R.O.C.

Tel: 886-2-8228 1100 Fax: 886-2-8228 6101

## **4 BAND GRAPHIC EQUALIZER PRE-AMP WITH SUBWOOFER OUTPUT**



**MODEL NO.: EMQ-P025**

**OEM and ODM orders are welcome**

- **4 BANDS GRAPHIC EQUALIZER WITH 12dB BOOST/ CUT**
- **SUBWOOFER FREQUENCY SELECTORS/OUTPUT-LEVEL CONTROL**
- **INPUT SELECTOR SWITCH THE RADIO INPUT OR CD INPUT**
- **PRE-AMP FADER OUTPUT FOR 4 CHANNEL SYSTEMS**
- **GOLD-PLATED RCA INPUT CONNECTORS**
- **OPTION TWO COLOR NIGHT LIGHT OR TRANSPARENT TOP COVER**

### **SPECIFICATIONS:**

**4-band Parametric: Bass 150Hz, Mid.-Bass 400Hz, Mid 2.5KHz, Hi 15KHz. Boost/Cut: 12dB. Subwoofer frequency: 43/60Hz Bandwidth: specific to each band-Hi Shelving. S/N ratio: 95dB/ REF 1V Input. THD: 0.05% Input sensitivity: 150mV. Input/Output Impedance: 20 K $\Omega$ /50K $\Omega$  Stereo Separation: 75dB/1KHz. Operating Voltage: 11-15V Negative ground. Size(H $\times$ W $\times$ D) :34m/m x 178m/m x 112m/m**

<http://www.easoco.com.tw>